



MeiG-SLM927

Smart LTE

Wi-Fi ax ready & BT 5.1

SLM927	600	SM6225	CPU	6nm	64bit ARM	8	CPU 4xA73 2.4GHz
& 4xA53 1.9GHz	Decode/encode	1080p@60fps		H.265/H.264		Android 13	
64GB+4GB	32GB+3GB	128GB+8GB		LTE CAT.4		TD-LTE/FDD-LTE/WCDMA/GSM	
BT	GNSS	WIFI					

SLM927		SLM927-CN	SLM927-EAU	SLM927-NA	SLM927-JP	SNM927.	
SLM927		LCM			UART	USB	I2C
SPI		2.4G/5G WiFi	BT	GPS			
POS	VR Camera						

✓

LTE

✓

WIFI

ax ready

✓

FHD+

1080x2520

@60Hz / 90Hz

✓

ISP

13+13+5MP


3

✓

GPS

✓

1080p @60fps









MeiG-SLM927

Smart LTE

Wi-Fi ax ready & BT 5.1

USB

: B B B
: B B B B B B
: B B

:
: 1 B
: B B B

B B B B

:
: B B B B
: B B B B B
:

:
: B B B B B B B
B B B B
:

&

-
-
-

1x 4-lane MIPI_DSI
FHD+ 1080x2520 @60Hz/90Hz

2C
(U)SIM 2 1.8V/2.95V
UART (4Mbps)
SD 1 SD 3.0, 4-bit SDIO
SPI
ADC 2
GPIO >19
PWRKEY 1.8V

Android 13

64GB + 4GB uMCP(LPDDR4x)
32GB + 3GB uMCP(LPDDR4x)
128GB + 8GB uMCP(LPDDR4x)

-30°C ~ +75°C
-40°C ~ +90°C
3.5V~4.35V 3.8V
41.0mm × 41.0mm × 2.6mm
LCC + LGA
13.0g

/FCC*/JATE*/TELEC*